

#### **TECHNICAL CHARACTERISTICS**

#### **SPECIFICATION**

50mA, 12VDC
100mOHM max.
20HM max.
min. 100MOHM at 500VDC
250VAC for 1 minute
0.25 + 0.2 mm / - 0.1 mm
10ms max.

## <u>MATERIAL</u>

 >Cover:
 Stainless Steel

 >Stem:
 LCP UL 94V-0

 >Frame:
 LCP UL 94V-0, color Black

 >Contact:
 Stainless Steel with silver

 >Terminal:
 Brass with silver plating

 >Tape:
 Polyimide tape

### SOLDERING INFORMATION

>Terminal in SMD version >Reflow soldering according to JEDEC J-STD 020 Hot Air >Hand soldering under 350°C for 3 sec. max

# WASHABLE DEFINITION

Please do not submerse washable products into water or cleaning agents or put them in locations exposed to water or liquids completely. When cleaning by hand (brushing), please do not use excessive force on our switch to avoid malfunction afterwards, because you could deform function relevant areas or you could damage sealing functions. Do not clean washable series immediately after soldering. The cleaning agent may be absorbed into the switch through respiration while the switch cools.

# **ENVIRONMENTAL**

Storage condition: -40°C ~ +85°C
 Operation condition: -40°C ~ +85°C
 Compliance: Lead Free, ROHS, Reach

# PACKAGING INFORMATION

>Tape & Reel

PN	Force	Color of Stem	Life cycle	
431 481 031 8 <sup>.</sup>	16 160g ± 50gf	Black	1.000.000	
431 471 031 82	26 260g ± 50gf	White	500.000	
431 471 031 83	36 360g ± 80gf	Salmon	500.000	

This electronic component is designed and developed with the intention for use in general electronics equipments.

Before incorporating the components into any equipments in the field such as aerospace, aviation, nuclear control, submarine, transportation, (automotive control, train control, ship control), transportation signal, disaster prevention, medical, public information network etc. where higher safety and reliability are especially required or if there is possibility of direct damage or injury to human body, Wurth Elektronik must be asked for a written approval.

In addition, even electronic component in general electronic equipments, when used in electrical circuits that require high safety, reliability functions or performance, the sufficient reliability evaluation-check for the safety must be performed before by the user before usage.

				GENERAL TOLERANCE .x = +/- 0,2 .xx = +/- 0,15			Basic ma	terial			
					Date	Name	DESCRIF	PTION			
f	remove Contact cladding	14-11-04	DaF	Drawn	10-09-30	Jelisarow	WS-TASV 6x6mm washable Tact Switch with ground termina				al
е	revisde MatchCode	14-07-24	AL	Checked	10-09-30	Hsu	SMD version				
d	Bounce 10ms max.	14-04-11	DaF								
С	washable definition	14-01-31	DaF	WE		ktronik	Scale	5:1	Position		SIZE
b	new values in chart	12-09-13	WJ	eiCan			Could	0.1			SIZE
a	warning text	11-10-28			eiCan		Drawing.	- No. 4314x10318	x6	A4	
REV	/ FILE	DATE	ΒY	EDV NO 4314x10311x6.dft					System :S	olid Edge V20	